

SHURE®

LEGENDARY
PERFORMANCE™

UHF-R® MW Wireless

A/A2/B 型対応 マルチチャンネル・ワイヤレスシステム



グループ／チャンネル一覧表
チャンネルプラン表

グループ／チャンネル一覧表 (単位 MHz)

A2型 (779.125 ~ 787.875MHz)

グループ チャンネル	L1	L2	L3	L4	L5	L6	L7	L8	H1	H2	H3	H4	H5	H6	H7	H8
A1	779.125	779.250	779.625	779.750	780.625	780.250	779.125	782.875	783.625	783.750	784.125	784.250	785.125	784.750	783.625	787.375
A2	779.375	779.500	779.875	780.500	781.125		779.375	783.000	783.875	784.000	784.375	785.000	785.625		783.875	787.500
A3	780.125	780.000	780.375	781.000	781.375		779.875	783.125	784.625	784.500	784.875	785.500	785.875		784.375	787.625
A4	780.750	780.875	781.250	782.125	781.750		780.500	783.250	785.250	785.375	785.750	786.625	786.250		785.000	787.750
A5	782.000	781.500	781.625	782.375	782.625		781.500	783.375	786.500	786.000	786.125	786.875	787.125		786.000	787.875
A6	782.500	781.875	782.250	782.750				782.375	783.500	787.000	786.375	786.750	787.250		786.875	
A7							782.750								787.250	

A型 (797.125 ~ 805.875MHz)

グループ チャンネル	L1	L2	L3	L4	L5	L6	L7	L8	H1	H2	H3	H4	H5	H6	H7	H8
1	797.125	797.250	797.625	797.750	798.625	798.250	797.125	800.875	801.625	801.750	802.125	802.250	803.125	802.750	801.625	805.375
2	797.375	797.500	797.875	798.500	799.125		797.375	801.000	801.875	802.000	802.375	803.000	803.625		801.875	805.500
3	798.125	798.000	798.375	799.000	799.375		797.875	801.125	802.625	802.500	802.875	803.500	803.875		802.375	805.625
4	798.750	798.875	799.250	800.125	799.750		798.500	801.250	803.250	803.375	803.750	804.625	804.250		803.000	805.750
5	800.000	799.500	799.625	800.375	800.625		799.500	801.375	804.500	804.000	804.125	804.875	805.125		804.000	805.875
6	800.500	799.875	800.250	800.750				800.375	801.500	805.000	804.375	804.750	805.250		804.875	
7							800.750								805.250	

B型 (806.125 ~ 809.750MHz)

グループ チャンネル	1	2	3	4	5	6	7
01	806.125	806.250	806.625	806.750	807.625	807.250	806.125
02	806.375	806.500	806.875	807.500	808.125		806.375
03	807.125	807.000	807.375	808.000	808.375		806.875
04	807.750	807.875	808.250	809.125	808.750		807.500
05	809.000	808.500	808.625	809.375	809.625		808.500
06	809.500	808.875	809.250	809.750			809.375
07							809.750

- * 7波以上を同時に使用する場合には、必ず以下の条件を守ってください。
 ◎送信機間を50cm以上離す。
 ◎受信機又はアンテナと送信機を5m以上離す。

- * グループL8及びグループH8は、L1～L7、H1～H7グループの使用法とは異なります。基本の組み合わせ以外の組み合わせにより、多チャンネル同時運用を可能にするための補助周波数です。したがってグループL8及びグループH8のチャンネルは同時使用できるものではありません。

A2型 (779.125 ~ 787.875MHz)

A2型	グループ番号							
Freq.	L1	L2	L3	L4	L5	L6	L7	L8
779.125	L1A1						L7A1	
779.250		L2A1						
779.375	L1A2						L7A2	
779.500		L2A2						
779.625			L3A1					
779.750				L4A1				
779.875			L3A2				L7A3	
780.000		L2A3						
780.125	L1A3							
780.250						L6A1		
780.375			L3A3					
780.500				L4A2			L7A4	
780.625					L5A1			
780.750	L1A4							
780.875		L2A4						
781.000				L4A3				
781.125					L5A2			
781.250			L3A4					
781.375					L5A3			
781.500		L2A5					L7A5	
781.625			L3A5					
781.750					L5A4			
781.875		L2A6						
782.000	L1A5							
782.125				L4A4				
782.250			L3A6					
782.375				L4A5			L7A6	
782.500	L1A6							
782.625					L5A5			
782.750				L4A6			L7A7	
782.875								L8A1
783.000								L8A2
783.125								L8A3
783.250								L8A4
783.375								L8A5
783.500								L8A6

A2型	グループ番号							
Freq.	H1	H2	H3	H4	H5	H6	H7	H8
783.625	H1A1							H7A1
783.750		H2A1						
783.875	H1A2							H7A2
784.000		H2A2						
784.125			H3A1					
784.250				H4A1				
784.375			H3A2					H7A3
784.500		H2A3						
784.625	H1A3							
784.750						H6A1		
784.875			H3A3					
785.000				H4A2				H7A4
785.125					H5A1			
785.250	H1A4							
785.375		H2A4						
785.500				H4A3				
785.625					H5A2			
785.750			H3A4					
785.875					H5A3			
786.000		H2A5						H7A5
786.125			H3A5					
786.250					H5A4			
786.375		H2A6						
786.500	H1A5							
786.625				H4A4				
786.750			H3A6					
786.875				H4A5				H7A6
787.000	H1A6							
787.125					H5A5			
787.250				H4A6				H7A7
787.375								H8A1
787.500								H8A2
787.625								H8A3
787.750								H8A4
787.875								H8A5

A 型 (797.125 ~ 805.875MHz)

A 型 Freq.	グループ番号							
	L1	L2	L3	L4	L5	L6	L7	L8
797.125	L11						L71	
797.250		L21						
797.375	L12						L72	
797.500		L22						
797.625			L31					
797.750				L41				
797.875			L32				L73	
798.000		L23						
798.125	L13							
798.250						L61		
798.375			L33					
798.500				L42			L74	
798.625					L51			
798.750	L14							
798.875		L24						
799.000				L43				
799.125					L52			
799.250			L34					
799.375					L53			
799.500		L25					L75	
799.625			L35					
799.750					L54			
799.875		L26						
800.000	L15							
800.125				L44				
800.250			L36					
800.375				L45			L76	
800.500	L16							
800.625					L55			
800.750				L46			L77	
800.875								L81
801.000								L82
801.125								L83
801.250								L84
801.375								L85
801.500								L86

A 型 Freq.	グループ番号							
	H1	H2	H3	H4	H5	H6	H7	H8
801.625	H11						H71	
801.750		H21						
801.875	H12						H72	
802.000		H22						
802.125			H31					
802.250				H41				
802.375			H32				H73	
802.500		H23						
802.625	H13							
802.750						H61		
802.875			H33					
803.000				H42			H74	
803.125					H51			
803.250	H14							
803.375		H24						
803.500				H43				
803.625					H52			
803.750			H34					
803.875					H53			
804.000		H25					H75	
804.125			H35					
804.250					H54			
804.375		H26						
804.500	H15							
804.625				H44				
804.750			H36					
804.875				H45			H76	
805.000	H16							
805.125					H55			
805.250				H46			H77	
805.375								H81
805.500								H82
805.625								H83
805.750								H84
805.875								H85

B 型 (806.125 ~ 809.750MHz)

B 型 Freq.	グループ番号						
	1	2	3	4	5	6	7
806.125	101						701
806.250		201					
806.375	102						702
806.500		202					
806.625			301				
806.750				401			
806.875			302				703
807.000		203					
807.125	103						
807.250						601	
807.375			303				
807.500				402			704
807.625					501		
807.750	104						
807.875		204					
808.000				403			
808.125					502		
808.250			304				
808.375					503		
808.500		205					705
808.625			305				
808.750					504		
808.875		206					
809.000	105						
809.125				404			
809.250			306				
809.375				405			706
809.500	106						
809.625					505		
809.750				406			707

* 枠内の英数字は、左からグループ/チャンネルを表しています。
例) L1A1 → A2 型 「L1」 グループ、「A1」 チャンネル

チャンネルプラン表 (UHF-RMW の送受信機のみで構成されているシステムの場合)

* 7 波以上を同時に使用する場合には、必ず以下の条件を守ってください。

◎送信機間を 50cm 以上離す。

◎受信機又はアンテナと送信機を 5m 以上離す。

A2 型 (779.125 ~ 787.875MHz)

A 型	グループ番号						
	39 波	34 波	27 波	23 波	18 波	18 波	10 波
Freq.	MW	A	2B	4B	A2	A4	B
779.125	MW/1	A/1	2B/1		A2/1		
779.250							
779.375							
779.500	MW/2		2B/2		A2/2		
779.625		A/2					
779.750	MW/3		2B/3		A2/3		
779.875							
780.000		A/3					
780.125	MW/4						
780.250		A/4			A2/4		
780.375							
780.500							
780.625	MW/5		2B/4		A2/5		
780.750							
780.875	MW/6				A2/6		
781.000							
781.125			2B/5				
781.250		A/5					
781.375	MW/7		2B/6				
781.500		A/6					
781.625					A2/7		
781.750							
781.875			2B/7				
782.000							
782.125		A/7					
782.250							
782.375		A/8					
782.500					A2/8		
782.625							
782.750					A2/9		
782.875	MW/8		2B/8				
783.000							
783.125					A2/10		
783.250							
783.375			2B/9				
783.500							
783.625							
783.750							
783.875	MW/9						
784.000					A2/11		
784.125	MW/10	A/9	2B/10				
784.250							
784.375		A/10					
784.500			2B/11		A2/12		
784.625	MW/11						
784.750			2B/12				
784.875							
785.000		A/11					
785.125					A2/13		
785.250		A/12	2B/13				
785.375							
785.500	MW/12		2B/14				
785.625							
785.750							
785.875	MW/13		2B/15				
786.000		A/13					
786.125	MW/14				A2/14		
786.250		A/14					
786.375							
786.500	MW/15						
786.625					A2/15		
786.750			2B/16				
786.875							
787.000	MW/16				A2/16		
787.125		A/15					
787.250	MW/17				A2/17		
787.375		A/16	2B/17				
787.500							
787.625					A2/18		
787.750	MW/18	A/17	2B/18				
787.875							

A 型 (797.125 ~ 805.875MHz)

A 型	グループ番号						
	39 波	34 波	27 波	23 波	18 波	18 波	10 波
Freq.	MW	A	2B	4B	A2	A4	B
797.125							A4/1
797.250							
797.375		A/18		4B/1			
797.500							A4/2
797.625	MW/19			4B/2			
797.750							A4/3
797.875		A/19					
798.000							
798.125	MW/20						
798.250		A/20					A4/4
798.375				4B/3			
798.500		A/21					
798.625				4B/4			A4/5
798.750	MW/21						
798.875							A4/6
799.000	MW/22			4B/5			
799.125							
799.250				4B/6			
799.375							
799.500	MW/23	A/22					
799.625							A4/7
799.750							
799.875		A/23					
800.000							
800.125	MW/24	A/24					
800.250							
800.375							
800.500	MW/25			4B/7			A4/8
800.625		A/25					
800.750							A4/9
800.875							
801.000	MW/26	A/26					
801.125							A4/10
801.250				4B/8			
801.375							
801.500							
801.625	MW/27			4B/9			
801.750							
801.875							
802.000							A4/11
802.125				4B/10			
802.250		A/27					
802.375	MW/28						
802.500				4B/11			A4/12
802.625		A/28					
802.750							
802.875							
803.000							
803.125				4B/12			A4/13
803.250							
803.375							
803.500							
803.625		A/29					
803.750							
803.875							
804.000	MW/29	A/30					
804.125							A4/14
804.250							
804.375				4B/13			
804.500		A/31					
804.625							A4/15
804.750	MW/30	A/32		4B/14			
804.875							
805.000	MW/31						A4/16
805.125							
805.250		A/33					A4/17
805.375	MW/32						
805.500				4B/15			
805.625		A/34					A4/18
805.750							
805.875							

B 型 (806.125 ~ 809.750MHz)

B 型	グループ番号						
	39 波	34 波	27 波	23 波	18 波	18 波	10 波
Freq.	MW	A	2B	4B	A2	A4	B
806.125				4B/16			B/1
806.250	MW/33		2B/19				
806.375							B/2
806.500	MW/34		2B/20	4B/17			
806.625							
806.750							B/3
806.875	MW/35		2B/21				
807.000							
807.125			2B/22				
807.250							B/4
807.375	MW/36						
807.500							
807.625							B/5
807.750				4B/18			
807.875							
808.000							
808.125	MW/37		2B/23	4B/19			
808.250							B/6
808.375				4B/20			
808.500							
808.625	MW/38		2B/24				
808.750				4B/21			B/7
808.875							
809.000			2B/25				B/8
809.125							
809.250			2B/26	4B/22			
809.375							B/9
809.500							
809.625	MW/39		2B/27	4B/23			B/10
809.750							

チャンネルプラン表 (UHF-RMW と UHF-R の送受信機が混在しているシステムの場合)

* 7 波以上を同時に使用する場合には、必ず以下の条件を守ってください。

◎送信機間を 50cm 以上離す。

◎受信機又はアンテナと送信機を 5m 以上離す。

A2 型 (779.125 ~ 787.875MHz)

A 型	グループ番号								
	7 波		8 波		10 波				
Freq.	C1	C2	C3	C4	C5	C6	C7	C8	C9
779.125	C11				C51				
779.250			C31			C61	C71	C81	
779.375	C12				C52				
779.500		C21		C41		C62			C91
779.625									
779.750			C32						
779.875		C22							
780.000				C42		C63	C72		
780.125					C53				
780.250									C92
780.375									
780.500			C33				C73		
780.625									
780.750				C43				C82	C93
780.875	C13								
781.000									
781.125									
781.250									
781.375						C64			
781.500							C74		
781.625					C54			C83	
781.750									C94
781.875	C14						C75		
782.000			C34					C84	
782.125									C95
782.250				C44					
782.375		C23							
782.500						C65			
782.625			C35						
782.750									
782.875									
783.000									
783.125									
783.250									
783.375						C66			
783.500									
783.625					C55			C85	
783.750	C15		C36						
783.875									
784.000				C45			C76		
784.125		C24							
784.250					C56			C86	C96
784.375									
784.500									
784.625									
784.750									
784.875						C67			
785.000									
785.125									
785.250									
785.375				C46	C57			C87	
785.500									
785.625							C77		
785.750			C37						
785.875									C97
786.000				C47					
786.125	C16					C68			
786.250									
786.375									
786.500		C25				C69			
786.625					C58				
786.750			C38				C78	C88	
786.875									
787.000				C48	C59				C98
787.125						C610			
787.250	C17							C89	
787.375							C79		
787.500		C26			C510			C810	
787.625							C710		C99
787.750		C27							
787.875									C910

A 型 (797.125 ~ 805.875MHz)

A 型	グループ番号								
	7 波		8 波		10 波				
Freq.	E1	E2	E3	E4	E5	E6	E7	E8	E9
797.125	E11				E51				
797.250			E31			E61	E71	E81	
797.375	E12				E52				
797.500		E21		E41		E62			E91
797.625									
797.750			E32						
797.875		E22							
798.000				E42		E63	E72		
798.125					E53				
798.250									E92
798.375									
798.500			E33				E73		
798.625									
798.750				E43				E82	E93
798.875	E13								
799.000									
799.125									
799.250						E64			
799.375									
799.500							E74		
799.625					E54			E83	
799.750									E94
799.875	E14						E75		
800.000			E34					E84	
800.125									E95
800.250				E44					
800.375		E23							
800.500						E65			
800.625			E35						
800.750									
800.875									
801.000									
801.125									
801.250									
801.375						E66			
801.500									
801.625					E55			E85	
801.750	E15		E36						
801.875									
802.000				E45			E76		
802.125		E24							
802.250					E56			E86	E96
802.375									
802.500									
802.625									
802.750									
802.875						E67			
803.000									
803.125									
803.250									
803.375				E46	E57			E87	
803.500									
803.625							E77		
803.750			E37						
803.875									E97
804.000				E47					
804.125	E16					E68			
804.250									
804.375									
804.500		E25				E69			
804.625					E58				
804.750			E38				E78	E88	
804.875									
805.000				E48	E59				E98
805.125						E610			
805.250	E17							E89	
805.375							E79		
805.500		E26			E510			E810	
805.625							E710		E99
805.750		E27							
805.875									E910

A型 (797.125 ~ 805.875MHz) +B型 (806.125 ~ 809.750MHz)

A型+B型	グループ番号									
	11波					12波				
	Freq.	F1	F2	F3	F4	F5	F6	F7	F8	F9
797.125	F11					F61			F91	
797.250		F21						F81		
797.375					F51	F62	F71			
797.500		F22						F82	F92	
797.625				F41			F72			
797.750					F52	F63				
797.875	F12							F83		
798.000				F42						
798.125										
798.250	F13									
798.375										
798.500										
798.625										
798.750		F23				F64				
798.875					F53		F73			
799.000			F31	F43						
799.125									F93	
799.250							F74			
799.375										
799.500		F24								
799.625								F84		
799.750	F14									
799.875						F65				
800.000										
800.125			F32						F94	
800.250				F44			F75			
800.375										
800.500										
800.625										
800.750										
800.875										
801.000							F76	F85		
801.125										
801.250										
801.375						F66				
801.500			F33							
801.625					F54					
801.750										
801.875	F15									
802.000				F45					F95	
802.125										
802.250		F25						F86		
802.375										
802.500										
802.625										
802.750		F26								
802.875	F16									
803.000							F77			
803.125										
803.250										
803.375										
803.500			F34	F46						
803.625						F67				
803.750										
803.875								F87		
804.000										
804.125					F55					
804.250	F17		F35						F96	
804.375						F68				
804.500										
804.625										
804.750									F97	
804.875						F69				
805.000								F88		
805.125		F27								
805.250							F78			
805.375										
805.500									F98	
805.625										
805.750										
805.875			F36					F89		

A型+B型	グループ番号									
	11波					12波				
	Freq.	F1	F2	F3	F4	F5	F6	F7	F8	F9
806.125						F56		F79		
806.250	F18									
806.375			F37		F57					
806.500										
806.625										
806.750	F19						F610			
806.875									F810	
807.000				F47						
807.125					F58					
807.250				F48						
807.375										
807.500										
807.625		F28								
807.750				F49	F59					
807.875										
808.000										F99
808.125			F38							
808.250										
808.375									F811	
808.500								F710		
808.625										F910
808.750		F29					F611			
808.875				F410						
809.000			F39		F510					
809.125								F711	F812	
809.250										
809.375		F210	F310							
809.500	F110				F511					F911
809.625			F311			F612	F712			
809.750	F111	F211		F411						F912

SHURE[®]
LEGENDARY
PERFORMANCE™

HIBINO

ヒビノインターサウンド株式会社

〒108-0075 東京都港区港南3-5-12 TEL: 03-5783-3880 FAX: 03-5783-3881

E-mail: info@hibino-intersound.co.jp <http://www.hibino-intersound.co.jp/>